

DYNAWELL Electronic Detonator Tester

Item	Part No.	Weight	Dimensions
Electronic Detonator Tester	2315414	1 kg	25x27,5x11,5cm



Technical Information

APPLICATION:
DESIGNED TO TEST DYNAENERGETICS RF-SAFE INITIATORS.

SPECIFICATIONS:

The **DYNAenergetics** Detonator Test Panel is designed to be a standalone product which can be used to test the RF-safe DYNAWELL electronic Detonators and Igniters For the test, a DC voltage is applied to the detonator and a series of LED's3 is provided to indicate the condition of the detonator.

The panel operates off a re-chargeable battery. A battery charger is provided to charge the batteries.

TECHNICAL DATA:

The connector: Banana Sockets
 Supply to panel: 1.5 W, Input Voltage 7.2 VDC
 Charger 100 VAC – 230 VAC, 50 – 60 Hz

Revision: IK00000AA

DYNAenergetics GmbH & Co. KG warrants only title to the equipment, products, materials and supplies and that the same are free from defects in workmanship and materials. There are no warranties, expressed or implied, of merchantability fitness or otherwise, which extend beyond those stated in the immediately preceding sentence. DYNAenergetics liability and Customer's remedy in any case of action arising out of the sale or use of any equipment, products, materials and supplies is expressly limited to the replacement of such equipment, products, materials and supplies on their return to DYNAenergetics or, at DYNAenergetics option, to the allowance to the Customer of credit for the cost of such items. In no event shall DYNAenergetics be liable for special, incidental, punitive or consequential damages.